

# On the Polarization Properties of the Far-Zone Radiation Fields of Primary and Secondary Electromagnetic Sources

N. Engheta, C. H. Papas  
 California Institute of Technology  
 Pasadena, California 91125  
 and  
 C. Elachi  
 Jet Propulsion Laboratory  
 California Institute of Technology  
 Pasadena, California 91109

The far-zone field of a transmitting antenna (primary source) resembles the far-zone field by a scattered (secondary source) in that each of the far-zone fields is a TEM wave travelling radially outward from a body of finite spatial extent. Choosing a spherical coordinate system centered on the body, (see Fig. 1) we note that in the far-zone of the body the electric vector has the form

$$\underline{E} = \text{Re}[\underline{e}_\theta F_\theta(\theta, \phi) + \underline{e}_\phi F_\phi(\theta, \phi)] \exp[i(kr - \omega t)]/4\pi r$$

where  $\underline{e}_\theta$ ,  $\underline{e}_\phi$  are unit vectors in the  $\theta$ ,  $\phi$  directions and  $F_\theta$ ,  $F_\phi$  are the components of the far-zone field amplitude. In terms of  $F_\theta$  and  $F_\phi$  the Stokes parameters of the far-zone field are

$$S_0 = \frac{1}{16\pi^2 r^2} (F_\theta F_\theta^* + F_\phi F_\phi^*), \quad S_1 = \frac{1}{16\pi^2 r^2} (F_\theta F_\theta^* - F_\phi F_\phi^*)$$

$$S_2 = \frac{1}{16\pi^2 r^2} (F_\theta F_\phi^* + F_\phi F_\theta^*), \quad S_3 = \frac{i}{16\pi^2 r^2} (F_\phi F_\theta^* - F_\theta F_\phi^*).$$

These parameters completely describe the polarization state of the far-zone field [1]. The purpose of the present paper is to report certain global properties the above Stokes possess over the surface of a far-zone sphere.

For  $S_0$  we have the following theorems:

Theorem I:  $S_0$  can not be constant over a far-zone sphere [2,3].

Theorem II:  $S_0$  can be determined over the entire far-zone sphere if  $S_0$  is known over a patch. This follows from the fact that  $F_\theta$  and  $F_\phi$  are entire functions of the complex variables  $\theta$  and  $\phi$ .

With the aid of Theorems I and II we see that  $S_0$  can not be constant even over a patch on the far-zone sphere for if it were constant over a patch it would be constant over the entire sphere.

Theorem III: The locus of  $S_0 = \text{constant}$  must be one or more closed curves or one or more isolated points on the far-zone sphere.




Fig. 1. A is a patch on the surface of a far-zone sphere. B is its complement i.e.  $A+B$  = the entire surface of the sphere. If  $S_i$  ( $i = 0, 1, 2, 3$ ) is known over region A, it can be extrapolated to all points of region B. However, if region A reduces to a curve segment, none of the four parameters can be extrapolated.

For  $S_1, S_2, S_3$  we have

Theorem IV: If  $S_i (i = 1, 2, 3)$  is constant over a patch, it must be constant over the entire sphere. However, since  $S_0^2 = S_1^2 + S_2^2 + S_3^2$  for monochromatic radiation [4] and since, as mentioned above,  $S_0$  can not be constant over a patch, only two of the three parameters  $S_1, S_2, S_3$  can be constant over a patch at the same time.

Theorem V: The locus of constant  $S_i (i = 1, 2, 3)$  must be one or more isolated points, one or more closed curves, or the entire sphere.

Theorem VI: From a knowledge of  $S_i (i = 1, 2, 3)$  over a patch its value over the entire sphere can be found by extrapolation, as in the case of  $S_0$ .

Wherever we have  $S_3 = 0$  on a far-zone sphere, the polarization is linear. This corresponds to what Müller calls a L-point [5]. Wherever we have  $S_1 = S_2 = 0$  on a far-zone sphere the polarization is circular. This is what Müller calls a C-point. Müller has shown that if all points of a patch are L-points, then all points of the entire sphere must be L-points. Clearly, this is a special case of our Theorem IV. He has also shown that if all points of a patch are C-points, then all points of the entire sphere must be C-points. This is also a special case of our Theorem IV.

In the design of antenna and radar systems the above theorems delimit the distribution of polarization over a far-zone sphere so that once the polarization over a patch has been specified the polarization over the rest of the sphere is fixed. For example, if at some point P on the far-zone sphere we have left-handed polarization and if at some other point Q on the far-zone sphere we have right-handed polarization, then along any path on the far-zone sphere that connects P and Q at least at one point along the path the polarization is unavoidably linear.

## REFERENCES

- [1] G. G. Stokes, "On the Composition and Resolution of Streams of Polarized Light from Different Sources," Trans. Cambridge Phil. Soc., 9:399 (1852). Reprinted in his "Mathematical and Physical Papers," vol. III, pp. 233-258, Cambridge University Press, London.
- [2] H. F. Mathis, "A Short Proof that an Isotropic Antenna is Impossible," Proc. IRE, 39, 970 (1951).
- [3] C. J. Bouwkamp, H. B. G. Casimir, "On Multipole Expansions in the Theory of Electromagnetic Radiation," Physica, 20, 539 (1954).

- [4] C. H. Papas, Theory of Electromagnetic Wave Propagation, McGraw-Hill Book Company, New York (1965).
- [5] C. Müller, Foundations of the Mathematical Theory of Electromagnetic Waves, Springer-Verlag, New York (1969).